

# Programmable Controller FP0R





## Pocket-size ultra-compact controller

### Features

- Large capacity program / data memory**  
 Program capacity: 32 k steps max.  
 Data register: 32 k words max.
- Ultra-high speed processing**  
 80 ns/step (ST instruction)  
 \* Within a range of 0 to 3,000 program steps
- USB tool port provided as standard equipment**  
 Capable of high-speed program transfer with USB 2.0
- Multi-axis control available without expansion units**  
 Built-in pulse outputs for four axes (50 kHz max. each)
- Battery-less automatic backup of all data**  
 The F type has a built-in FeRAM, that allows the automatic saving of all data without a backup battery.
- Makeover for FP0R analog units. Greatly improved performance, extended functions**  
 Higher resolution: 14 bits (previously 12 bits)  
 Up to 8-channel input: Easier transition to multi-channel systems.

### SPECIFICATIONS

| Product type of FP0R control unit   |   | C10<br>(Relay output type only)   | C14<br>(Relay output type only)   | C16<br>(Transistor output type only)  | C32<br>(Transistor output type only)            | T32<br>(Transistor output type only)                                | F32<br>(Transistor output type only) |  |
|-------------------------------------|---|---|---|---|---|---|--------------------------------------|--|
| Programming method / Control method |   | Relay symbol / Cyclic operation   |   |   |   |   |                                      |  |
| Number of I/O points                | Control unit only (No expansion)                                    | 10 points<br>[Input: 6, Relay Output: 4]  | 14 points<br>[Input: 8, Relay Output: 6]  | 16 points<br>[Input: 8, Transistor Output: 8]                                 | 32 points<br>[Input: 16, Transistor Output: 16] | 32 points<br>[Input: 16, Transistor Output: 16]                     |                                      |  |
|                                     | With expansion 1<br>Same type of control and expansion units (Note) | Max. 58 points  | Max. 62 points  | Max. 112 points   | Max. 128 points                                 | Max. 128 points   |                                      |  |
|                                     | With expansion 2<br>Mix type of relay and transistor units (Note)   | Max. 106 points   | Max. 110 points   | Max. 112 points   | Max. 128 points                                 | Max. 128 points   |                                      |  |
| Program memory                      |   | EEPROM (no backup battery required)   |   |   |   |   |                                      |  |
| Program capacity                    |   | 16 k steps  |   |   | 32 k steps                                      |   |                                      |  |
| Number of instructions              | Basic instructions  | 110 types approx.   |   |   |   |   |                                      |  |
|                                     | High-level instructions   | 210 types approx.   |   |   |   |   |                                      |  |
| Operation speed                     |   | Up to 3,000 steps<br>3,001st. and later steps   |   |   |   |   |                                      |  |
|                                     |   | Basic instructions: 0.08 $\mu$ s min. Timer instructions: 2.2 $\mu$ s min. High-level instructions: 0.32 $\mu$ s (MV instruction) min.<br>Basic instructions: 0.58 $\mu$ s min. Timer instructions: 3.66 $\mu$ s min. High-level instructions: 1.62 $\mu$ s (MV instruction) min.             |   |   |   |   |                                      |  |
| Operation memory                    | Relay   | Internal relay (R)  |   | 4,096 points  |   |   |                                      |  |
|                                     |   | Timer / Counter (T/C)   |   | 1,024 points  |   |   |                                      |  |
|                                     | Memory area   | Data register (DT)  |   |   | 32,765 words                                    |   |                                      |  |
|                                     |   | Index register (IX, IY)   |   |   | 14 words (IO to ID)                             |   |                                      |  |
| Master control relay points (MCR)   |   | 256 words   |   |   |   |   |                                      |  |
| Number of labels (JMP and LOOP)     |   | 256 labels  |   |   |   |   |                                      |  |
| Differential points                 |   | Equivalent to the program capacity  |   |   |   |   |                                      |  |
| Number of step ladder               |   | 1,000 stages  |   |   |   |   |                                      |  |
| Number of subroutines               |   | 500 subroutines   |   |   |   |   |                                      |  |
| Special functions                   | High speed counter  | Single-phase: 6 points (50 kHz max. each) 2-phase: 3 channels (15 kHz max. each) (Note)   |   |   |   |   |                                      |  |
|                                     | Pulse output  | Not available   |   | 4 points (50 kHz max. each) 2 channels can be controlled individually. (Note) |   |   |                                      |  |
|                                     | PWM output  | Not available   |   | 4 points (6 Hz to 4.8 kHz)  |   |   |                                      |  |
|                                     | Pulse catch input / interrupt input                                 | Total 8 points (with high speed counter)  |   |   |   |   |                                      |  |
|                                     | Interrupt program   | Input: 8 programs (6 programs for C10 only) / Periodic: 1 program / Pulse match: 4 programs   |   |   |   |   |                                      |  |
|                                     | Periodical interrupt  | In units of 0.5 ms: 0.5 ms to 1.5 sec. / In units of 10 ms: 10 ms to 30 sec.  |   |   |   |   |                                      |  |
|                                     | Constant scan   | In units of 0.5 ms: 0.5 ms to 600 ms  |   |   |   |   |                                      |  |
| RS-232C port                        |   | One RS-232C port is mounted on each of C10CRS, C10CRM, C14CRS, C14CRM, C16CT, C16CP, C32CT, C32CP, T32CT, T32CP, F32CT and F32CP type (3P terminal block) Transmission speed (Baud rate): 2,400 to 115,200 bits/sec., Transmission distance: 15 m 9.843 ft. Communication method: half duplex |   |   |   |   |                                      |  |
| Maintenance                         | Memory backup   | Program and system register   |   |   |   | Stored program and system register in EEPROM                        |                                      |  |
|                                     |   | Operation memory  |   |   |   | Backup of the entire area by FeRAM (without the need for a battery) |                                      |  |
|                                     |   |   | Stored fixed area in EEPROM<br>Counter: 16 points<br>Internal relay: 128 points<br>Data register: 315 words |   |   |   |                                      |  |
|                                     | Self-diagnostic function  |   | Watchdog timer (690 ms approx.), program syntax check   |   |   |   |                                      |  |
|                                     | Real-time clock function  |   | Not available   |   |   |   | Available                            |  |
| Other functions                     |   | Rewriting in RUN mode, download in RUN mode (incl. comments) 8-character password setting, and program upload protection  |   |   |   |   |                                      |  |

Note: For the limitations while operating units, refer to the manual.

## Disclaimer

The applications described in the catalog are all intended for examples only. The purchase of our products described in the catalog shall not be regarded as granting of a license to use our products in the described applications. We do NOT warrant that we have obtained some intellectual properties, such as patent rights, with respect to such applications, or that the described applications may not infringe any intellectual property rights, such as patent rights, of a third party.

**Panasonic**  
INDUSTRY

**Panasonic Industry Co., Ltd.**

Industrial Device Business Division  
7-1-1, Morofuku, Daito-shi, Osaka 574-0044, Japan  
[industrial.panasonic.com/ac/e/](http://industrial.panasonic.com/ac/e/)