



TEL (915) 590-8500  
FAX (915) 590-8510

4.63"

**SIEMENS**  
Cat No. HF262 Fusible Heavy Duty Safety Switch Type VBII  
60 Amps Maximum 600 Volts AC (V~) Maximum 600 Volts DC (V=) Maximum  
Type 1 Indoor

Horsepower Ratings	240 VAC 1Ø	240 VAC 3Ø	480 VAC 1Ø	480 VAC 3Ø	600 VAC 1Ø	600 VAC 3Ø	250 VAC	600 VDC
Std. HP (Std. Fuse) <sup>4</sup>	3		5		10		10	25
Max. HP (Time Delay)	10		20		25			30

Continuous load current not to exceed 80% of the rating of fuses employed in other than motor circuits.  
Suitable for use as Service Equipment when used with ground bar kit **HG61234** on 3 phase, 3 wire systems or when used with **HN623** neutral kit on 1 phase, 3 wire or 3 phase, 4 wire systems.

**Fuse and Short Circuit Information**  
When used with Class K fuses, Class H fuses or a UL Listed Circuit Breaker rated for 10,000 amperes, RMS symmetrical, **600** volts maximum, this switch is suitable for use on a circuit capable of delivering not more than 10,000 amperes, RMS symmetrical, **600** volts, maximum.  
When used with Class R fuses and Class R fuse clip kit **HR62** properly installed, this switch is suitable for use on a circuit capable of delivering not more than 200,000 amperes, RMS symmetrical, **600** volts maximum.  
When used with Class J fuses with the load base relocated to the "J Fuse" position marked on the enclosure this switch is suitable for use on a circuit capable of delivering not more than 200,000 amperes, RMS symmetrical, **600** volts maximum.  
**Danger** - Unless class R or J fuses are used, this switch may present a risk of fire and injury to persons if installed on circuits capable of delivering more than 10,000 amperes, RMS symmetrical.  
When used with fuses marked with DC ratings, this switch is suitable for use on a circuit capable of delivering not more than the DC interrupting rating marked on the fuse, at the DC voltage rating marked on the fuse, up to a maximum of 10,000 amperes, **600** volts DC.  
**Danger** - Unless fuses marked for an interrupting rating of 10,000 amperes at **600** volts DC are used, this switch may present a risk of fire and injury to persons if installed on circuits capable of delivering more than 10,000 amperes.

**Renewable link fuses are not recommended**

**⚠ DANGER**

**Hazardous Voltage. Will cause death or serious injury.**

- Disconnect and lock out power supplying this switch before working on this switch.
- Turn off switch before removing or installing fuses if so equipped.
- Always use a properly rated voltage sensing device on all fuse clips (Fusible) or all load side terminals (Non-Fusible) to confirm switch is off.
- Close or replace cover before turning power on.

**Terminal & Wire Information USE 60°C / 75°C COPPER OR ALUMINUM WIRE**

Description	Wire Range	Wire Tightening Torque <sup>5</sup>	Lug Mounting Torque <sup>6</sup>
Line, Load & Main Neutral	14-2 AWG	35 lb-ins, 14-10 AWG / 40 lb-ins, 8 AWG 45 lb-ins, 6-4 AWG / 50 lb-ins, 3-2 AWG	80 lb-ins.
Service Ground	14-4 AWG	35 lb-ins, 14-10 AWG / 40 lb-ins, 8 AWG 45 lb-ins, 6-4 AWG	24 lb-ins.

Inspection record number:

**UL Listed Compression Lugs (Refer to manufacturers instructions for proper installation)<sup>6</sup>**

Wire Size (AWG OR kcmil)	Burdny		Thomas & Betts		Ilscro	
	CU ONLY	CU/AL	CU ONLY	CU/AL	CU ONLY	CU/AL
14-10			256-30695-1352	60097		
8	YA8C-L1 BOX YA8C-TC14	YA8CA3	54130 54930BE	60102 61102		ACL-8
6	YA6C-L BOX YA6C	YA6CA1	54105 54905BE	60107 61107	CRB-6 CRB-6L	ACL-6
4			54106	61112	CRB-4	

Accessories	HA161234	Neutral	HN623	Class R Fuse Kit (Rejects Class H & K Fuses)	HR62
Aux. Switch (1NO-1NC)	HA261234	Ground Lug Kit (Wire Range 14-4 AWG)	HG61234	Class T Fuse Kit	
Aux. Switch (2NO-2NC)	HA361234	Isolated Ground Lug Kit	HG261234	Fuse Puller Kit (3 per kit)	HP62
Low voltage Aux. Sw. (1NO-1NC)	HCL623	Wire Grip Kit (CU)	HLC612	Shield Kit	HSK62SSW

Replacement Parts	HFB62	Wire Grip Kit (AL)	HL612	Handle/Handle Guard	HH6123
Line Base	HBB62	Mechanism	HM6123	Door	HF262DOOR

Protected by one or more of the following US Patents: 6,134,979, 6,356,460, 5,945,650, 5,990,439.  
<sup>4</sup> The starting current of motors more than the standard horsepower or kilowatt ratings may require the use of fuses with appropriate time delay characteristics.  
<sup>5</sup> When tightening or replacing connectors, refer to lug mounting torque in Terminal & Wire Information Table.  
<sup>6</sup> If compression lugs are used for the neutral, order compression lug neutral barrier kit **HCL623**.

For questions on this device please call 1-800-241-4453  
Siemens Industry, Inc.  
Norcross, GA 30092 USA  
<http://www.usa.siemens.com/powerdistribution>  
Assembled in Mexico  
Pc. No. 502086X07

R .125"  
X4

<b>COMPANY NAME</b>			Due to the variances among computer monitors and printers, the depictions of the colors you see may not be a true representation of the final color job, these colors are only for proofing. If close color matching is a requirement of the job, then you must let us know at the beginning of the job and specify PMS colors or otherwise provide color samples.						
<b>SIEMENS INDUSTRY/MTR</b>			<b>JOB WILL NOT BE PRINTED UNLESS APPROVED BY CUSTOMER.</b>			PART NO. <b>502086X07</b> <b>A7B91501321678</b>			
THIS DOCUMENT IS THE PROPERTY OF LABELTECH, INC. IT'S USE IS AUTHORIZED ONLY FOR RESPONDING TO A REQUEST FOR QUOTATION OR FOR THE PERFORMANCE OF WORK REQUESTED FROM LABELTECH, INC. ALL QUESTIONS MUST BE REFERRED TO THE LABELTECH, INC. PRODUCTION DEPARTMENT.	<b>MATERIAL</b>		<b>SIZE</b>		<input type="checkbox"/> OK TO PRINT AS IS <input type="checkbox"/> MAKE CORRECTIONS, RESUBMIT CORRECTED PROOF  <input type="checkbox"/> OK TO PRINT WITH CORRECTIONS AS MARKED		DWG NO. <b>500443; 501010 41P</b>		
	<b>SYNTHETIC PAPER</b>		<b>WIDTH</b>				DESCRIPTION: <b>INTERIOR LABEL</b>		
<b>Lamination: No</b>		<b>4.63"</b>		<b>AUTHORIZED BY</b>		<b>DATE</b>		<b>REVISION LEVEL 41P</b>	
<b>INK COLORS</b>		<b>LENGTH</b>				<b>DESIGNER</b>		<b>Joel Ortega</b>	
<b>Black</b>		<b>8.50"</b>		<b>CHECKED BY</b>		<b>DATE</b>		<b>07/10/12</b>	
<b>Red 185</b>		<b>ROUND CORNER RADIUS</b>		<b>DATE</b>		<b>REVISION LEVEL 41P</b>		<b>DESIGNER</b>	
<b>.125"</b>		<b>LENGTH</b>		<b>DATE</b>		<b>REVISION LEVEL 41P</b>		<b>DESIGNER</b>	