

International **IR** Rectifier

Bulletin I27101 rev. B 04/98

IRK. SERIES

THYRISTOR/ DIODE and THYRISTOR/THYRISTOR

INT-A-pak™ Power Modules

Features

- High voltage
- Electrically isolated base plate
- 3000 V_{RMS} isolating voltage
- Industrial standard package
- Simplified mechanical designs, rapid assembly
- High surge capability
- Large creepage distances
- UL E78996 approved 


135 A
140 A
160 A

Description

These series of INT-A-paks modules uses high voltage power thyristors/ diodes in seven basic configurations. The semiconductors are electrically isolated from the metal base, allowing common heatsinks and compact assemblies to be built. They can be interconnected to form single phase or three phase bridges or as AC-switches when modules are connected in anti-parallel. These modules are intended for general purpose applications such as battery chargers, welders and plating equipment and where high voltage and high current are required (motor drives, U.P.S., etc.).

Major Ratings and Characteristics

Parameters	IRK.135.. IRK.136..	IRK.141.. IRK.142..	IRK.161.. IRK.162..	Units
I _{T(AV)}	135	140	160	A
@ T _C	85	85	85	°C
I _{T(RMS)}	300	310	355	A
I _{TSM} @ 50Hz	3200	4750	5100	A
@ 60Hz	3360	5000	5350	A
I ² t @ 50Hz	51.5	113	131	KA ² s
@ 60Hz	47	103	119	KA ² s
I ² /t	515	1130	1310	KA ² /s
V _{DRM} /V _{RRM}	upto1600	upto2000	upto1600	V
T _J range	-40 to 130	-40 to 125		°C



IRK.135, .136, .141, .142, .161, .162 Series

Bulletin I27101 rev. A 09/97

 International
 Rectifier

ELECTRICAL SPECIFICATIONS
Voltage Ratings

Type number	Voltage Code	V_{RRM} , maximum repetitive peak reverse voltage V	V_{RSM} , maximum non-repetitive peak reverse voltage V	I_{RRM} max. @ 150°C mA
IRK.135, IRK.136 IRK.161, IRK.162	04	400	500	50
	08	800	900	
	12	1200	1300	
	14	1400	1500	
	16	1600	1700	
IRK.141, IRK.142	08	800	900	50
	12	1200	1300	
	16	1600	1700	
	18	1800	1900	
	20	2000	2100	

Forward Conduction

Parameter	IRK.135. IRK.136.	IRK.141. IRK.142.	IRK.161. IRK.162.	Units	Conditions
$I_{T(AV)}$ Max. average on-state current @ Case temperature	135	140	160	A	180° conduction, half sine wave
	85	85	85	°C	
$I_{T(RMS)}$ Max. RMS on-state current	300	310	355	A	as AC switch
I_{TSM} Maximum peak, one-cycle on-state, non-repetitive surge current	3200	4750	5100	A	Sine half wave, Initial $T_J = T_J$ max.
	3360	5000	5350		
	2700	4000	4300		
	2800	4200	4500		
I^2t Maximum I^2t for fusing	51.5	113	131	KA ² s	Initial $T_J = T_J$ max.
	47	103	119		
	36	80	92		
	33	73	84		
$I^2\sqrt{t}$ Maximum $I^2\sqrt{t}$ for fusing	515	1130	1310	KA ² \sqrt{s}	$t = 0.1$ to $10ms$, no voltage reapply
$V_{T(TO)1}$ Low level value of threshold voltage	0.98	0.75	0.79	V	$(16.7\% \times \pi \times I_{T(AV)} < I < \pi \times I_{T(AV)})$, @ T_J max.
$V_{T(TO)2}$ High level value of threshold voltage	101	0.86	0.92		$(I > \pi \times I_{T(AV)})$, @ T_J max.
r_{f1} Low level value on-state slope resistance	1.62	0.92	0.64	mΩ	$(16.7\% \times \pi \times I_{T(AV)} < I < \pi \times I_{T(AV)})$, @ T_J max.
r_{f2} High level value on-state slope resistance	1.56	0.77	0.49		$(I > \pi \times I_{T(AV)})$, @ T_J max.
V_{FM} Maximum forward voltage drop	1.66	1.32	1.26	V	$I_{FM} = \pi \times I_{F(AV)} \times T_J = \text{max.}, 180^\circ \text{ conduction}$ $\text{Av. power} = V_{F(TO)} \times I_{F(AV)} + r_f \times (I_{F(RMS)})^2$
I_H Maximum holding current		500		mA	Anode supply = 12V initial $I_T = 30A$, $T_J = 25^\circ C$
I_L Maximum latching current		300		mA	Anode supply = 12V resistive load = 1Ω gate pulse: 10V, 100μs, $T_J = 25^\circ C$

Switching

Parameter	IRK.135. IRK.136.	IRK.141. IRK.142.	IRK.161. IRK.162.	Units	Conditions
t_d	Typical delay time	2.0	1.0	1.0	μs $T_J = 25^\circ C$ Gate Current = 1A $dIg/dt = 1A/\mu s$
t_r	Typical rise time	3.0	2.0	2.0	μs $T_J = 25^\circ C$ $Vd = 0.67\% V_{DRM}$
t_q	Typical turn-off time		50 - 150	μs	$I_{TM} = 300 A$; $-dI/dt = 15 A/\mu s$; $T_J = T_J \text{ max}$ $V_f = 50 V$; $dV/dt = 20 V/\mu s$; Gate 0 V, 100Ω

Blocking

Parameter	IRK.135. IRK.136.	IRK.141. IRK.142.	IRK.161. IRK.162.	Units	Conditions
I_{RRM} I_{DRM}	Maximum peak reverse and off-state leakage current		50	mA	$T_J = 150^\circ C$
V_{INS}	RMS isolation voltage		3000	V	50Hz, circuit to base, all terminals shorted, $t = 1s$
dv/dt	critical rate of rise of off-state voltage		1000	V/ μs	$T_J = T_J \text{ max.}$, exponential to 67% rated V_{DRM}

Triggering

Parameter	IRK.135. IRK.136.	IRK.141. IRK.142.	IRK.161. IRK.162.	Units	Conditions
P_{GM}	Max. peak gate power	5	10	10	W $tp \leq 5ms$, $T_J = T_J \text{ max.}$
$P_{G(AV)}$	Max. average gate power	1	2	2	W $f=50Hz$, $T_J = T_J \text{ max.}$
I_{GM}	Max. peak gate current	2	3	3	A $tp \leq 5ms$, $T_J = T_J \text{ max.}$
$-V_{GT}$	Max. peak negative gate voltage	5	5	5	V
V_{GT}	Max. required DC gate voltage to trigger	4.0 3.0 2.0	4.0 3.0 2.0	V T _J =-40°C T _J =25°C T _J =T _J max.	Anode supply = 12V, resistive load; Ra = 1Ω
I_{GT}	Max. required DC gate current to trigger	350 200 100	350 200 100	mA T _J =-40°C T _J =25°C T _J =T _J max.	Anode supply = 12V, resistive load; Ra = 1Ω
V_{GD}	Max. gate voltage that will not trigger	0.25	0.30	0.30	V @ $T_J = T_J \text{ max.}$, rated V_{DRM} applied
I_{GD}	Max. gate current that will not trigger	10	10	10	mA
di/dt	Max. rate of rise of turned-on current	300	500	500	A/ μs @ $T_J = T_J \text{ max.}$, $I_{TM} = 400A$ rated V_{DRM} applied

Thermal and Mechanical Specifications

Parameter	IRK.135. IRK.136.	IRK.141. IRK.142.	IRK.161. IRK.162.	Units	Conditions
T_J	Max. junction operating temperature range	-40 to 130	-40 to 150	°C	
T_{sg}	Max. storage temperature range		-40 to 150	°C	
R_{thJC}	Max. thermal resistance, junction to case	0.20	0.17	0.17	K/W DC operation, per junction
R_{thCS}	Max. thermal resistance, case to heatsink		0.035	K/W	Mounting surface smooth, flat and greased Per module
T	Mounting IAP to heatsink torque ± 10% busbar to IAP	4 to 6	4 to 6	Nm	A mounting compound is recommended and the torque should be rechecked after a period of 3 hours to allow for the spread of the compound. Lubricated threads.
wt	Approximate weight	500 (17.8)		g (oz)	

IRK.135, .136, .141, .142, .161, .162 Series

Bulletin I27101 rev. A 09/97

International
IR Rectifier

ΔR Conduction (per Junction)

(The following table shows the increment of thermal resistance R_{thJC} when devices operate at different conduction angles than DC)


Devices	Sinusoidal conduction @ T_J max.					Rectangular conduction @ T_J max.					Units
	180°	120°	90°	60°	30°	180°	120°	90°	60°	30°	
IRK.135, IRK.136	0.016	0.019	0.024	0.035	0.060	0.011	0.019	0.026	0.037	0.060	K/W
IRK.141, IRK.142	0.016	0.019	0.025	0.036	0.060	0.012	0.020	0.027	0.037	0.060	
IRK.161, IRK.162	0.015	0.019	0.024	0.036	0.060	0.012	0.020	0.027	0.037	0.060	

INT-A-paks Suitable for Current Source Inverters

Thyristor		Diode	$I_{T(AV)} / I_{F(AV)} @ T_C$		
V_{DRM}	V_{RSM}	V_{RRM}	135A @ 85°C	140A @ 85°C	160A @ 85°C
1400	1500	2000	IRKH135-14D20 IRKH136-14D20	IRKH141-14D20 IRKH142-14D20	IRKH161-14D20 IRKH162-14D20
1400	1500	2000	IRKL135-14D20 IRKL136-14D20	IRKL141-14D20 IRKL142-14D20	IRKL161-14D20 IRKL162-14D20
1600	1700	2500	IRKH135-16D25 IRKH136-16D25	IRKH141-16D25 IRKH142-16D25	IRKH161-16D25 IRKH162-16D25
1600	1700	2500	IRKL136-16D25	IRKL142-16D25	IRKL161-16D25 IRKL162-16D25
1800	1900	2800	Not Available	IRKH141-18D28	Not Available
1800	1900	2800	Not Available	IRKL141-18D28	Not Available
2000	2100	3200	Not Available	IRKH141-20D32	Not Available
2000	2100	3200	Not Available	IRKH142-20D32	Not Available
			Not Available	IRKL141-20D32	Not Available
			Not Available	IRKL142-20D32	Not Available

For all other parameters and characteristics refer to standard IRKH... and IRKL... modules.

Application Notes



Ordering Information Table

Device Code		IRK	T	16	2	-	16	D25	N
1		(1)	(2)	(3)	(4)		(5)	(6)	(7)
1	- Module type								
2	- Circuit configuration								
3	- Current rating: $I_{T(AV)} \times 10$ rounded								
4	- For IRK.13. only:								
	5 = option with spacers and longer terminal screws								
	6 = option with standard terminal screws								
	For IRK.14. and IRK.16. only:								
	1 = option with spacers and longer terminal screws								
	2 = option with standard terminal screws								
5	- Voltage code: Code x 100 = V_{RRM} (See Voltage Ratings Table)								
6	- Current Source Inverters types (See Table)								
7	- None = Standard devices								
	N = Aluminum nitride substrate								

Outline Table

	<ul style="list-style-type: none"> - All dimensions in millimeters (inches) - Dimensions are nominal - Full engineering drawings are available on request - UL identification number for gate and cathode wire: UL 1385 - UL identification number for package: UL 94V0 					
	<ul style="list-style-type: none"> - All dimensions in millimeters (inches) - Dimensions are nominal - Full engineering drawings are available on request - UL identification number for gate and cathode wire: UL 1385 - UL identification number for package: UL 94V0 					
For all types	A	B	C	D	E	
IRK...5 & ...1	25 (0.98)	----	----	41 (1.61)	47 (1.85)	
IRK...6 & ...2	23 (0.91)	30 (1.18)	36 (1.42)	----	----	
IRKT...	IRKH...	IRKL...	IRKU...	IRKV...	IRKK...	IRKN...

NOTE: To order the Optional Hardware see Bulletin I27900

IRK.135, .136, .141, .142, .161, .162 Series

Bulletin I27101 rev. B 04/98

International
IR Rectifier




Fig. 1 - Current Ratings Characteristics




Fig. 2 - Current Ratings Characteristics




Fig. 3 - On-state Power Loss Characteristics




Fig. 4 - On-state Power Loss Characteristics




Fig. 5 - Maximum Non-Repetitive Surge Current




Fig. 6 - Maximum Non-Repetitive Surge Current




Fig. 7 - On-state Power Loss Characteristics




Fig. 8 - On-state Power Loss Characteristics




Fig. 9 - On-state Power Loss Characteristics

IRK.135, .136, .141, .142, .161, .162 Series

Bulletin I27101 rev. B 04/98

International
IR Rectifier




Fig. 10 - On-state Voltage Drop Characteristics




Fig. 11 - Reverse Recovery Charge Characteristics




Fig. 12 - Current Ratings Characteristics




Fig. 13 - Current Ratings Characteristics




Fig. 14 - On-state Power Loss Characteristics




Fig. 15 - On-state Power Loss Characteristics




Fig. 16 - Maximum Non-Repetitive Surge Current




Fig. 17 - Maximum Non-Repetitive Surge Current




Fig. 18 - On-state Power Loss Characteristics




Fig. 19 - On-state Power Loss Characteristics

IRK.135, .136, .141, .142, .161, .162 Series

Bulletin I27101 rev. B 04/98

International
IR Rectifier




Fig. 20 - On-state Power Loss Characteristics




Fig. 21 - On-state Voltage Drop Characteristics




Fig. 22 - Reverse Recovery Charge Characteristics




Fig. 23 - Current Ratings Characteristics




Fig. 24 - Current Ratings Characteristics




Fig. 25 - On-state Power Loss Characteristics




Fig. 26 - On-state Power Loss Characteristics




Fig. 27 - Maximum Non-Repetitive Surge Current




Fig. 28 - Maximum Non-Repetitive Surge Current




Fig. 29 - On-state Power Loss Characteristics

IRK.135, .136, .141, .142, .161, .162 Series

Bulletin I27101 rev. B 04/98

International
IR Rectifier




Fig. 30 - On-state Power Loss Characteristics




Fig. 31 - On-state Power Loss Characteristics




Fig. 32 - On-state Voltage Drop Characteristics




Fig. 33 - Reverse Recovery Charge Characteristics




Fig. 34 - Thermal Impedance Z_{thJC} Characteristics




Fig. 35 - Gate Characteristics




Fig. 36 - Gate Characteristics