CM-SE-600 1/3



PRODUCT-DETAILS

CM-SE-600

CM-SE-600 Screw-in bar electrode 600mm, for compact support KH-3



General Information	
Extended Product Type	CM-SE-600
Product ID	1SVR450056R0100
EAN	4013614347115
Catalog Description	CM-SE-600 Screw-in bar electrode 600mm, for compact support KH-3
Long Description	The CM-SE-600 is a screw-in bar electrode for compact support CM-KH-3. This screw-in bar electrode is 600 mm long

Ordering		
EAN	4013614347115	
Minimum Order Quantity	1 piece	
Customs Tariff Number	90261089	

Popular Downloads		
Data Sheet, Technical Information	2CDC110004C0210_02	
Instructions and	2CDC110004C0207_02	

CM-SE-600 2/3

				_	١.
IV	ıa	n	u	a	lς

CAD Dimensional	2CDC001079B0201
Drawing	

Dimensions		
Product Net Width	4 mm	
Product Net Height	600 mm	
Product Net Depth / Length	4 mm	
Product Net Weight	0.059 kg	

Technical	
Function	Accessory - Screw in electrode CM-SE-600
	600 mm for compact support CM-KH-3
Sub-Function	Screw in electrode 600 mm for compact support CM-KH-3

Material Compliance	
Conflict Minerals Reporting Template (CMRT)	9AKK108467A5658
REACH Declaration	1SVD981001-4501
RoHS Information	1SVD981001-4401
RoHS Status	Following EU Directive 2011/65/EU
Toxic Substances Control Act - TSCA	1SVD981001-4501

Certificates and Declarations		
Declaration of Conformity - CE	1SVD981075-00	
Declaration of Conformity - UKCA	1SVD981075-10	

Container Information		
Package Level 1 Units	box 1 piece	
Package Level 1 Width	4 mm	
Package Level 1 Depth / Length	4 mm	
Package Level 1 Height	600 mm	
Package Level 1 Gross Weight	0.059 kg	
Package Level 1 EAN	4013614347115	

Classifications		
ETIM 7	EC002498 - Accessories for low-voltage switch technology	
ETIM 8	EC001447 - (Fill) level monitoring relay	
ETIM 9	EC001447 - (Fill) level monitoring relay	
eClass	V11.0 : 27371813	

CM-SE-600 3/3

UNSPSC	39121436
E-Number (Finland)	2712878
E-Number (Norway)	4187293

Categories

 $Low\ Voltage\ Products\ and\ Systems \rightarrow Control\ Products \rightarrow Electronic\ Relays\ and\ Controls \rightarrow Liquid\ Level\ Monitors\ and\ Controls$

