




---

 PRODUCT-DETAILS

# CR308BT941A1AAL1A

## 308 Combo Starter-CR308BT941A1AAL1A Combination Motor Starter




---

**General Information**

Global Commercial Alias	CR308BT941A1AAL1A
Extended Product Type	308 Combo Starter-CR308BT941A1AAL1A
Product ID	7GSP019936R0006
Catalog Description	308 Combo Starter-CR308BT941A1AAL1A Combination Motor Starter
Long Description	Combination, Full-Voltage Motor Starter for single-speed induction motors for upto 400hp, 600V. Provide short Circuit protection by fuse, circuit breaker or MCP.

---

**Ordering**

Minimum Order Quantity	1 EA
Customs Tariff Number	85365040
Product Main Type	NEMA Motor Starter

---

**Dimensions**

Product Net Width	10 in
Product Net Depth / Length	24 in

Product Net Height	8.63 in
Product Net Weight	19 lb

### Technical

Enclosure Type NEMA	Type1
Number of Poles	3

### Technical UL/CSA

NEMA Size	0
-----------	---

### Material Compliance

WEEE B2C / B2B	Business To Business
WEEE Category	4. Large Equipment (Any External Dimension More Than 50 cm)

### Certificates and Declarations

cULus Certificate	E1811
UL Certificate	E1811

### Container Information

Package Level 1 Units	1 piece
Package Level 1 Width	11.75 in
Package Level 1 Depth / Length	25.5 in
Package Level 1 Height	11.75 in
Package Level 1 Gross Weight	19 lb

### Classifications

eClass	V11.1 : 27371216
ETIM 6	EC000225 - Control circuit devices combination in enclosure
ETIM 7	EC000225 - Control circuit devices combination in enclosure
ETIM 8	EC000225 - Control circuit devices combination in enclosure
UNSPSC	39121521

---

## Categories

---

Low Voltage Products and Systems → Control Products → Contactor Starters → NEMA Enclosed Starters

